

COMPACT PRINTER for balances/scales

AD-8127

NEW!!



- ✓ Easy setting and operation with a numeric keypad and LCD display
- ✓ Built-in calendar and clock for printing date and time at any time
- ✓ Sends re-zero and weighing data request commands to the balance/scale

(Continued)



A&D ...Clearly a Better Value
A&D Company, Limited
<http://www.aandd.jp>

- ✓ Clear and visible dot matrix printing, which also enables long-term preservation of the printed records
- ✓ Compact and lightweight for portability and installation anywhere
- ✓ Interval printing mode for printing weighing data at set intervals
- ✓ Chart printing mode for printing time-series variations of weighing data
- ✓ Dump printing mode to receive and print GLP/GMP/GCP/ISO compliant output from the balance/scale
- ✓ Performs and prints the results of statistical calculation including standard deviation
- ✓ Prints an ID number set for the printer at any time
- ✓ Dust-free paper (AX-PP173-S) available for use in clean rooms
- ✓ Two types of RS-232C cables (D-Sub 25P and D-Sub 9P) provided as standard to connect to balances/scales with different interfaces*
- ✓ Receives a print, paper feed, print statistical calculation results, print total, re-zero, or weighing data request command from the optional foot switch (AX-SW128)

Specifications

Character specifications	7 × 9 dots, 1.6 (W) × 3.2 (H) mm
Printing speed	Approx. 1.6 lines/second
Paper feeding speed	Approx. 4 lines/second
Number of characters printed	24 characters/line
Printer paper width	57.5 mm
Operating environment	0 to 40 °C/32 to 104 °F, 35 to 85%RH (no condensation)
Storage environment	-20 to 60 °C/-4 to 140 °F, 10 to 90%RH (no condensation)
Interface	RS-232C (D-Sub 9P, male) / Current loop (DIN)
Power supply	AC adapter
Size / weight	174 (W) × 141 (D) × 87 (H) mm / approx. 500 g
Standard accessories	Ink ribbon (1 pc), plain printer paper (1 roll), AC adapter, AC adapter label, instruction manual, two RS-232C cables (D-Sub 25P and D-Sub 9P)*

Accessories

- AX-PP137-S Plain printer paper (10 rolls)
- AX-PP173-S Dust-free printer paper (10 rolls)
- AX-ERC-22B Ink ribbon (5 pcs)



A&D Company, Limited

3-23-14 Higashi-Ikebukuro, Toshima-ku, Tokyo 170-0013 JAPAN
 Telephone:[81](3) 5391-6132 Fax:[81](3) 5391-6148
<http://www.aandd.jp>

A&D ENGINEERING, INC.

1756 Automation Parkway, San Jose, CA 95131 U.S.A.
 Telephone:[1](408) 263-5333 Fax:[1](408) 263-0119

A&D Australasia Pty Ltd.

32 Dew Street, Thebarton, South Australia 5031 AUSTRALIA
 Telephone:[61](8) 8301-8100 Fax:[61](8) 8352-7409

A&D INSTRUMENTS LTD.

Unit 24/26 Blacklands Way Abingdon Business Park,
 Abingdon, Oxon OX14 1DY UNITED KINGDOM
 Telephone:[44](1235) 550420 Fax:[44](1235) 550485

<German Sales Office>

Hamburger Straße 30 D-22926 Ahrensburg GERMANY
 Telephone:[49](0) 4102 459230 Fax:[49](0) 4102 459231

A&D KOREA Limited

817, Manhattan Bldg., 33, Gukjegeumyung-ro 6-gil,
 Yeongdeungpo-gu, Seoul, 07331, KOREA
 Telephone:[82](2) 780-4101 Fax:[82](2) 782-4280

A&D RUS CO., LTD.

Vereyskaya str.17, Moscow, 121357 RUSSIA
 Telephone: [7] (495) 937-33-44 Fax: [7] (495) 937-55-66

A&D Instruments India Private Limited

509 Udyog Vihar Phase V
 Gurgaon-122 016, Haryana, INDIA
 Telephone: [91](124) 471-5555 Fax: [91](124) 471-5599